

Tablet Alarm

Mains or battery powered remote controlled alarm unit for use with tablets.

Contents

Tablet Alarm complete with holder
Power Supply

Installation

The alarm can be secured using the adhesive pad located on the base or fixing with screws.

Firstly clean the surface where the alarm is being placed. Remove the backing from the adhesive pad and press it down firmly onto the surface. If fixing with screws first remove the alarm from the holder by pressing down on the tab on the left hand side and slide the alarm backwards. This will give you access to the screw holes for the self-tapping screws (not supplied). Once the holder is secured to the surface, slide the alarm back until it clicks into position.

The alarm features an anti-tamper switch which will activate the alarm if your alarm is removed.

To secure a tablet to the alarm, remove the backing from the adhesive pad on the sensor and secure this to the back of the tablet. If the optional charging cable is not being used please ensure the terminator is connected

Instructions

Mains Powered

Connect power supply to the alarm and you will hear a beep and the LED on the sensor will be continuously lit showing power to the sensor. The tablet can now be charged.

When using a charging lead, first remove the terminator from the bottom edge of the sensor and connect the compatible lead for the device. The tablet is now being charged even though the alarm is turned off.

Turn the alarm on by holding the remote control 1cm from the infrared receiver at the back of the alarm and pressing the button. The alarm will give one long beep and the green LED on the pod will be lit continuously showing it is powered. The alarm is now armed.

If the tablet is removed, the alarm will sound and the red LED will flash. Turn the alarm off by holding the remote control 1cm from the infrared receiver at the back of the alarm and pressing the button. The alarm will beep 3 times and the alarm is now turned off. This will then allow you to resolve the issue. Reset the alarm as above.



Unit 5 Fullwood Close, Aldermans Green Industrial Estate, Coventry CV2 2SS
Tel: 024 76603535 Fax: 024 76603636
Website: www.myriadtec.com

If the alarm is removed from its holder the anti-tamper switch will activate the alarm and the green LED will flash. Turn the alarm off as above and rectify the issue. Reset the alarm as above.

Battery Powered

Turn the alarm on by holding the remote control 1cm from the infrared receiver at the back of the alarm and pressing the button. The alarm will give one long beep and the green LED will light up then flash every 10 seconds. The alarm is now armed.

If the tablet is removed the alarm will sound and the red LED will flash. Turn the alarm off by holding the remote control 1cm from the infrared receiver at the back of the alarm and pressing the button. The alarm will beep 3 times and it is now turned off. This will then allow you to resolve the issue.

If the alarm is removed from its holder the anti-tamper switch will activate the alarm and the green LED will flash. Turn the alarm off as above and rectify the issue. Reset the alarm as above.

To reset the alarm hold the remote control 1cm from the infrared receiver at the back of the alarm and press the button. The alarm will give one long beep and the green LED will light up once and flash every 10 seconds. The alarm is now armed.

If the battery is low, the LED on the base will flash and the alarm will beep indicating the battery needs to be replaced immediately. Ensure the alarm is turned off when changing the battery.

To replace the battery (3v Lithium Coin Cell CR2450M). Remove the alarm from the holder by pressing the tab on the side of the holder and sliding the alarm backwards. Carefully remove the 2 screws to gain access to the battery cover. Open the battery compartment, remove the old battery and fit the new battery. Replace the bracket ensuring it is facing the correct way and slide the alarm back into the holder until it clicks into position. Reset the alarm as above.

Optional extras are available upon request. Please contact us using the details below for more information.



Unit 5 Fullwood Close, Aldermans Green Industrial Estate, Coventry CV2 2SS
Tel: 024 76603535 Fax: 024 76603636
Website: www.myriadtec.com